

PowerTech Products Menu
A PowerTech Menu Utility

Installation Guide

For Technical Support and Product Information:

Phone:	+1-253-872-7788
Toll Free:	+1-800-915-7700
Fax:	+1-253-872-7904
E-Mail:	support@powertech.com
Corporate Office:	6703 S. 234th Street Kent, WA 98032

Do you have a tough time remembering all the different commands to start up the PowerTech products?

PowerTech has responded to this all-too-common dilemma by developing a new menu utility for PowerTech customers. This new menu utility (**PowerTech Products Menu**) provides a single interface (or master menu) for convenient access to PowerTech product main menus.

The PowerTech products that can be accessed through the **PowerTech Products Menu** interface include:

- PowerTech Network Security
- PowerTech Authority Broker
- PowerTech Compliance Monitor
- PowerTech Security Audit
- PowerTech Password Control
- PowerTech Interact

Installation of 'PowerTech Products Menu'

The **PowerTech Products Menu** utility is installed as an LPP and takes only a few minutes to install. Installation can be performed either as a CD install, or a Web Download install, and instructions for both are provided below.

CD Install

__1) Place the CD in your System i CD drive. Enter the following at the IBM OS Main Menu:

RSTLICPGM LICPGM(1PTUT01) DEV(OPT01)

```
MAIN                                i5/OS Main Menu                                System:  DOUDERA

Select one of the following:

    1. User tasks
    2. Office tasks
    3. General system tasks
    4. Files, libraries, and folders
    5. Programming
    6. Communications
    7. Define or change the system
    8. Problem handling
    9. Display a menu
   10. Information Assistant options
   11. iSeries Access tasks

   90. Sign off

Selection or command
==> RSTLICPGM LICPGM(1PTUT01) DEV(OPT01)

F3=Exit  F4=Prompt  F9=Retrieve  F12=Cancel  F13=Information Assistant
F23=Set initial menu
(C) COPYRIGHT IBM CORP. 1980, 2005.
```

Press **'Enter'**.

--OR--

WEB Download Install

__1) At the IBM OS Main Menu command line enter:

RSTLICPGM

Press **'F4'**.

The following RSTLICPGM dialog will be presented.

```
RSTLICPGM
Restore Licensed Program (RSTLICPGM)

Type choices, press Enter.

Product . . . . . > 1PTUT01      Character value
Device . . . . . > *SAVF         Name, *SAVF
                        + for more values
Optional part to be restored . . *BASE      *BASE, 1, 2, 3, 4, 5, 6, 7...
Type of object to be restored . *ALL       *ALL, *PGM, *LNG
Language for licensed program . *PRIMARY   Character value, *PRIMARY...
Output . . . . . *NONE         *NONE, *PRINT
Release . . . . . *FIRST       Character value, *FIRST
Replace release . . . . . *ONLY    Character value, *ONLY, *NO
Save file . . . . . P1PTUT01    Name
  Library . . . . . QGPL        Name, *LIBL, *CURLIB

More...

F3=Exit   F4=Prompt   F5=Refresh   F10=Additional parameters   F12=Cancel
F13=How to use this display   F24=More keys
```

Enter the following in the dialog (as shown above).

Product: **1PTUT01**
Device: ***SAVF**
Save file: **P1PTUT01**
Library: **QGPL**

Press **'Enter'**.

__2) Next, the Software Agreement for the **PowerTech Products Menu** utility will be presented. Scroll to review the Agreement. You must accept the Agreement to proceed with the installation. Press **'F14'** to accept the Agreement. *(If you do not want to accept the Agreement, press 'F16' to decline and the **PowerTech Products Menu** utility will not be installed.)*

'PowerTech Products Menu' Software Agreement

```
Software Agreement
System: DOUDERA
Licensed program . . . . . : 1PTUT01
Licensed program option . . . . . : *BASE
Release . . . . . : V1ROM0

(C) COPYRIGHT The PowerTech Group, Inc. 2007

The PowerTech Group, Inc.
6703 S. 234th Street
Kent, WA 98032 USA

Phone: +1-253-872-7788
Toll Free: +1-800-915-7700 (U.S. and Canada)
email: support@powertech.com
Website: http://www.powertech.com

More...
F3=Exit F6=Print F12=Cancel F13=Select available language F14=Accept
F16=Decline F17=Top F18=Bottom
```

After accepting the agreement, the message: *'Software agreement accepted. Install of licensed program is continuing.'* will be displayed at the bottom of the screen as the install continues.

When the installation of the **PowerTech Products Menu** utility has completed, the IBM OS Main Menu will be presented and a message confirming installation will be displayed at the bottom of the screen (as shown in the screenshot below).

Installation confirmation message

```
MAIN i5/OS Main Menu
System: DOUDERA
Select one of the following:

1. User tasks
2. Office tasks
3. General system tasks
4. Files, libraries, and folders
5. Programming
6. Communications
7. Define or change the system
8. Problem handling
9. Display a menu
10. Information Assistant options
11. iSeries Access tasks

90. Sign off

Selection or command
===> _____

F3=Exit F4=Prompt F9=Retrieve F12=Cancel F13=Information Assistant
F23=Set initial menu
*PGM objects for product 1PTUT01 option *BASE release *FIRST restored. +
```

Now that the **PowerTech Products Menu** utility has been installed, you can access all the PowerTech product main menus conveniently via the **PowerTech Products Menu** interface.

Accessing 'PowerTech Products Menu'

To access the '**PowerTech Products Menu**', simply enter the following command at the IBM OS Main Menu command line:

GO POWERTECH

The 'PowerTech Products Menu' will be presented (shown below). The menu options allow you to access PowerTech product main menus and display product information.

PowerTech Products Menu

```
POWERTECH                PowerTech Products Menu                System:  OLDGLORY
Select one of the following:
    1. Work with Network Security
    2. Work with Authority Broker
    3. Work with Compliance Monitor
    4. Work with Security Audit
    5. Work with Password Control
    6. Work with Interact
    20. Display Product Information
Selection or command
===> _____
F3=Exit  F4=Prompt  F9=Retrieve  F12=Cancel
(C) COPYRIGHT The PowerTech Group, Inc. 2007.
```

Determining if a PowerTech Product is Installed and/or Licensed

If any of the PowerTech products listed in the 'PowerTech Products Menu' is not installed on the same system that the **PowerTech Products Menu** utility is installed, the option number for that product will be replaced with an '*', and the menu option color text will change.

Additionally, if a product is installed but not licensed, to the left of the option number a '>' will be displayed. In that event, you may be able to access the product menu but the product may not be fully functional.

In the example shown below, a `>` is displayed to the left of option 2, indicating that Authority Broker is installed, but not licensed on this system. An `*` is also displayed, instead of an option number, to the left of the Security Audit and Password Control products, indicating that these products are not installed on the system.

Examples: (`>` = product installed but not licensed) and (`*` = product not installed)

```
POWERTECH                               PowerTech Products Menu
                                           System:   DOUDERA

Select one of the following:

    1. Work with Network Security
  >  2. Work with Authority Broker
    3. Work with Compliance Monitor
   * 4. Work with Security Audit
   * 5. Work with Password Control
    6. Work with Interact

    20. Display Product Information

Selection or command
===> _____

F3=Exit  F4=Prompt  F9=Retrieve  F12=Cancel
(C) COPYRIGHT The PowerTech Group, Inc. 2007.
```

'PowerTech Products Menu' Options

The 'PowerTech Products Menu' provides the following options:

1. [Work with Network Security](#)
2. [Work with Authority Broker](#)
3. [Work with Compliance Monitor](#)
4. [Work with Security Audit](#)
5. [Work with Password Control](#)
6. [Work with Interact](#)
20. [Display Product Information](#)

Option 1. Work with Network Security

Selecting option '1' from the 'PowerTech Products Menu' will present the 'PowerTech Network Security Main Menu'.

PowerTech Network Security Main Menu

```
Date: 1/18/08          PowerTech Network Security      Syst: LIMEKILN
Time: 10:47:44          Main Menu                    Menu: LNS400
                                                User: CATHERINEB

Select one of the following:
 1. Work with PowerTech Network Security Servers
 2. Work with PowerTech Network Security by User
 3. Work with PowerTech Network Security by Location or IP Address
 4. Work with IP Address Groups
 5. Work with Network Security Reporting Groups

10. Work with Captured Transactions
11. Work with Memorized Transactions

80. PowerTech Network Security Reports Menu
81. PowerTech Network Security Administration Menu
82. PowerTech's Utilities Menu

Selection or command
===> _____

F3=Exit   F4=Prompt   F9=Retrieve   F12=Cancel
F13=Information Assistant   F16=AS/400 main menu
```

Comprehensive information on the Network Security Main Menu options can be found in the PowerTech Network Security Administrator's Guide.

Option 2. Work with Authority Broker

Selecting option '2' from the 'PowerTech Products Menu' will present the 'PowerTech Authority Broker Main Menu'.

PowerTech Authority Broker Main Menu

```
Date: 1/18/08          PowerTech Authority Broker      Sys : OLDGLORY
Time: 10:43:16          Main Menu                    Menu: MAIN
                                                User: CATHERINEB
                          Authority Broker Full License Version

Working on System OLDGLORY for Partition 0

Select one of the following:
 1. Assign System Users to Switch Profiles
 2. Run Authority Broker Event Reports
 3. Give a user FireCall access to Authority Broker
 4. Use Authority Broker Reports Menu
 5. Use Authority Broker Configuration Menu

Selection or command
===> _____

F3=Exit   F4=Prompt   F5=Refresh   F9=Retrieve   F12=Cancel
(C) COPYRIGHT The PowerTech Group, Inc. 2004 - 2007
```

Comprehensive information on the Authority Broker Main Menu options can be found in the PowerTech Authority Broker Administrator's Guide.

Option 3. Work with Compliance Monitor

Selecting option '3' from the 'PowerTech Products Menu' will present the 'PowerTech Compliance Monitor Menu'.

PowerTech Compliance Monitor Menu

```
PTCMMENU                PowerTech Compliance Monitor Menu                System:  OLDGLORY
Select one of the following:

  Compliance Monitor Consolidator
    1. Start Consolidator Monitor
    2. Stop Consolidator Monitor
    3. Request Configuration Assessment
    4. Change Administrator Password
    5. Display Consolidator Log File

  Compliance Monitor Endpoint
    11. Start Endpoint Monitor
    12. Stop Endpoint Monitor

Selection or command
===> _____

F3=Exit  F4=Prompt  F9=Retrieve  F12=Cancel
(C) COPYRIGHT The PowerTech Group, Inc. 2007.
```

Comprehensive information on the Compliance Monitor Menu options can be found in the PowerTech Compliance Monitor Administrator's Guide.

Option 4. Work with Security Audit

Selecting option '4' from the 'PowerTech Products Menu' will present the 'PowerLock Security Audit Main Menu'.

PowerLock Security Audit Main Menu

```
Date: 1/18/08                PowerLock SecurityAudit                Sys : OLDGLORY
Time: 10:40:29                Main Menu                                Menu: PLSA1000
                                PowerLock SecurityAudit Full License Version  User: CATHERINEB

Working on System OLDGLORY for Partition 0
Select one of the following:
  1. System values menu
  2. User menu

  11. Library menu
  12. Object menu
  13. Adopt authority menu
  14. Command menu
  15. Device menu
  16. Output queue menu

  22. Network menu

More...

Selection or command
===> _____

F3=Exit  F4=Prompt  F5=Refresh  F9=Retrieve  F12=Cancel
F13=Work with Submitted Jobs  F14=Work with Spooled Files  F15=Display Message
(C) COPYRIGHT The PowerTech Group, Inc. 2001-2006
```

Comprehensive information on the Security Audit Main Menu options can be found in the PowerTech Security Audit Administrator's Guide.

Option 5. Work with Password Control

Selecting option '5' from the 'PowerTech Products Menu' will present the 'Password Control Main Menu'.

Password Control Main Menu

```
PTPCMAIN                Password Control Main Menu                System:  OLDGLORY
Select one of the following:
    1. Update encrypted word list
    2. Run weak passwords report
   10. Add/Remove password validation program
   20. Administration Menu

Selection or command
===> _____

F3=Exit  F4=Prompt  F9=Retrieve  F12=Cancel
(C) COPYRIGHT The PowerTech Group, Inc., 2007.
```

Comprehensive information on the Password Control Main Menu options can be found in the *PowerTech Password Control Administrator's Guide*.

Option 6. Work with Interact

Selecting option '6' from the 'PowerTech Products Menu' will present the 'PowerTech Interact Main Menu'.

PowerTech Interact Main Menu

```
Date: 1/18/08                PowerTech Interact                Syst: LIMEKILN
Time: 10:49:45                Main Menu                        Menu: PLIMAIN
                                Licensed Version                    User: CATHERINEB

Working on System LIMEKILN for Partition 0
Select one of the following:
    1. Work with Brokers/Agents
    2. Work with Monitors Menu
    3. Configuration Menu

Selection or command
===> _____

F3=Exit  F4=Prompt  F5=Refresh  F9=Retrieve  F12=Cancel
(C) COPYRIGHT The PowerTech Group, Inc. 2002-2008
```

Comprehensive information on the Interact Main Menu options can be found in the *PowerTech Interact Administrator's Guide*.

Option 20. Display Product Information

Selecting option '20' from the 'PowerTech Products Menu' will present the 'Display Product Information' dialog.

Display Product Information

```
Display Product Information (PTPRDVRM)

Type choices, press Enter.

Product ID . . . . . _____ 1PLCMT2, 1PLCMT3, 3PLAB00...
Output . . . . . * _____ *, *PRINT

F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys
```

The Display Product Information (PTPRDVRM) command displays information about the System i and a specified product. This information can be displayed on the screen or directed to a spool file that can then be printed or downloaded to a text file.

Product ID specifies the Licensed Program Product (LPP) ID.

Output specifies the output type.

Output type includes:

- '*' = Output is shown on the display.
- ***PRINT** = The output is printed with the job's spooled output.